



Thunder 185 ESP – RC82 A/B/C

2 piece stringing

Recommended string is Ektelon SynGut 16 gauge

String Pattern 12 x 16 Power Ring

Length 20' Mains x 16' Crosses

Suggested tension range is 34 +/- 4

Mains skip holes at 5H & 7H

Tie off Mains at 6H

Tie off Crosses at 3HR & 2TR

String over the Power Ring on the left side and under the Power Ring on the right side

Helpful hint: when stringing certain main strings, insert a piece of scrap string before pulling tension in order to help expose cross holes. Before pulling tension on the cross strings, the scrap strings should be removed.

Mains

1. Start at top of racquet and insert 10' of string from 1HR to Power Ring (PR) around to 2HR
2. Clamp string at 1HR, but do not pull tension yet
3. Feed other end of string from 1HL to Power Ring (PR) around to 2HL, tension and clamp
4. Tension and clamp string at 2HR
5. Feed string from 2HR to 3HR down to PR around to 4HR, tension and clamp
6. Feed string from 2HL to 3HL down to PR around to 4HL, tension and clamp
7. Feed string from 4HR to 6HR down to PR around to 8HR, tension and clamp
8. Feed string from 4HL to 6HL down to PR around to 8HL, tension and clamp
9. Tie off mains at 6HL & 6HR

Crosses

1. Tie starting knot at 3HR and feed string from 5HR across to 5HL, tension and clamp
2. Feed string from 5HL to 7HL across to 7HR, tension and clamp
3. Continue stringing crosses conventionally and tie off at 2TR